



WA-320 (VHF 200MHz)



Main Features:

- . Power output: 20W
- . With full range Hi-Fi speaker
- . Module type: Crystal quartz locked control two unbalanced 6.3mm jack inputs for microphone sensitivity
- . One unbalanced 6.3mm jack for AUX/CD sensitivity, REC. out
- . Mic.1 input could be automatically switched to wire and wireless mic.
- . With battery-rechargeable function for Hand-held / Bodypack microphone

SPECIFICATION

Model	WA-320
Channel	Single Channel
Frequency band	VHF Hi band 160 ~ 245 Mhz
Receiver type	Non-Diversity
Receiving mode	Quartz controlled fixed frequency
Power output	20 W
Frequency response	150~15KHz (±3 dB)
Frequency stability	±0.005%
Modulation mode	FM (F3E)
S/N Ratio	MIC. 1,2 : ??5 dB ; AUX : ??0 dB
Input / sensitivity	MIC 1,2 / 2.5mV ; AUX/ 150 mV
Power supply	DC 12V/ 115 or 230 V AC adapter
12V DC supply	10W
Rec. Output	REC. OUT/ 280 mA/ unblanced
Preamplifier output	0 dB 600Ω
Battery	8 pcs ("D" size)
Color	WHITE/ BLACK
Dimensions	220(W)x145(D)x270(H)mm; (8.7"x5.7"x10.6")
Weight	4.0kg (8.8 lb)